



# RF



## ORANGE COUNTY AMATEUR RADIO CLUB, INC.

VOL. XLIV NO. 7

P.O. BOX 3454, TUSTIN, CA 92861-3454

July 2003

### The Prez Sez:

Field Day for 2003 is over, the bands were not very good but everyone enjoyed themselves. (see PIX below) With the pre-planning of Larry K6VDP, Ken W6HHC, Bob KD6BWH, Elmer WA6PFA and Bob AF6C the operations went like clock work. A big thanks to Bruce KC6DLA, Bob KD6XO and Rich KE6WWK for the use of their Motor Homes. Don Hughes thankfully made time from his busy schedule to ensure that we were fed. Old friend Chris Breller, KJ6ZH, made the long trip down from the Bay Area to do some satellite

work and Chris KE6LEX finished up his night school and was a welcome sight with his solar power set up. To the rest of the members a great big hand for helping set up and tear down all the towers and antennas. We had several HAMS that were giving us a hand, who were not club members and they made our Field Day even more successful. Thank you and the door is always open to you. We also had a nice visit from ARRL Vice President Fried Heyn WA6WZO, SW Director Art Goddard W6XD and Assistant Director Tuck Miller NZ6T.

### July Meeting

**Don't forget that the meeting will start one-half hour early at 7:00 PM, due to Red Cross new security rules.**

The presentation by Joe Moell KØOV this meeting will be:

### **"Radio Direction Finding"**

Hams and their families are having fun with radio direction finding. You can learn about mobile T-hunting, radio-orienting, ARDF and ROCAs.

Don't miss it. All members and visitors are welcome.

The next general meeting will be:

**Friday, July 18th  
@ 7:00 PM**

We will be meeting in Anaheim Room in the east **Red Cross** Bldg.



### **In This Issue: Page**

The PREZ SEZ	.....1
FIELD DAY group shot	.....1
July Speaker " <b>KØOV on RDF</b> "	1
CLUB INFORMATION	.....2
TechTalk : Antenna Tuners	.....3
FD Pictures Collage	.....5
Field Day Scores	.....6
June General Meeting	.....7
July Board Meeting	.....7
"Young Ham of the Year"	.....8
BPL Interference Threat	.....9
Keep Morse Code Reqrmnts?...	9
Quotes from FD 2003	.....10

**THE ORANGE COUNTY  
AMATEUR RADIO CLUB,  
INC.**

P.O. Box 3454, Tustin, CA 92781



**2003 Board of Directors:**

**President:**

Lowell Burnett, KQ6JD  
(714) 997-0999  
[LBur729028@aol.com](mailto:LBur729028@aol.com)

**Vice President:**

Steve Brody, KB1GZ  
(714) 974-0338  
[stevebrody@sbcglobal.net](mailto:stevebrody@sbcglobal.net)

**Secretary:**

David Mofford, W7KTS  
(714) 285-0693  
[davidmofford@hotmail.com](mailto:davidmofford@hotmail.com)

**Treasurer:**

Phil Andersen, N7PA  
(949) 492-1900  
[n7pa@arrl.net](mailto:n7pa@arrl.net)

**Membership:**

Bob Buss, KD6BWH  
(714) 534-2995  
[kd6bwh@aol.com](mailto:kd6bwh@aol.com)

**Activities:**

Matt McKenzie, K6LNX  
(714) 546-2228  
[k6lnx@arrl.net](mailto:k6lnx@arrl.net)

**Publicity:**

Larry Hoffman, K6LDC  
(714) 636-4345  
[k6ldc@earthlink.net](mailto:k6ldc@earthlink.net)

**Technical:**

Bob Eckweiler, AF6C  
(714) 639-5074  
[af6c@arrl.net](mailto:af6c@arrl.net)

**Members At Large:**

Cory Terando, AE6GW  
(714) 894-3817  
[corymuzk@yahoo.com](mailto:corymuzk@yahoo.com)

Frank Smith, WA6VKZ  
(714) 356-4695  
[wa6vkz@msn.com](mailto:wa6vkz@msn.com)

**2003 Club Appointments:**

**W6ZE Club License Trustee:**

Bob Eckweiler, AF6C  
(714) 639-5074  
[af6c@arrl.net](mailto:af6c@arrl.net)

**Club Historian:**

Bob Evans, WB6IXN  
(714) 543-9111  
[bobev@netzero.net](mailto:bobev@netzero.net)

**RF Editor:**

Ken Konechy, W6HHC  
(714) 744-0217  
[kkonechy@pacbell.net](mailto:kkonechy@pacbell.net)

**WEB Master:**

Ken Konechy, W6HHC  
(714) 744-0217  
[kkonechy@pacbell.net](mailto:kkonechy@pacbell.net)

**ARRL Assistant Director:**

Ken Konechy, W6HHC  
(714) 744-0217  
[kkonechy@pacbell.net](mailto:kkonechy@pacbell.net)

**ARRL Awards Appointee:**

Larry Beilin, K6VDP  
(714) 557-7217  
[k6vdp@aol.com](mailto:k6vdp@aol.com)

**OCCARO Delegate:**

Bob Buss, KD6BWH  
(714) 534-2995  
[kd6bwh@aol.com](mailto:kd6bwh@aol.com)

**Monthly Events:**

**General Meeting:**

Third Friday of the month  
at 7:00 PM  
American Red Cross  
(near Tustin Ave & 4th St)  
Santa Ana, CA

**Club Breakfast:**

First Saturday of the month  
at 8:00 AM  
CowGirl's Cafe, Too  
2610 S. Harbor Blvd  
(just south of Warner)  
Santa Ana, CA

**Club Nets (Listen for W6ZE):**

7.115 ± MHz CW OCNW  
Sun- 9:00 AM – 10 AM  
Rick KF6UEB, Net Control

28.375 ± MHz SSB  
Wed- 7:30 PM - 8:30 PM  
Bob AF6C, Net Control

146.55 MHz Simplex FM  
Wed- 8:30 PM - 9:30 PM  
Bob, WB6IXN, Net Control

**VISIT OUR WEB SITE**

<http://www.w6ze.org>

for up-to-the-minute club information, the latest membership rosters, special activities, back issues of RF, links to ham-related sites, vendors and manufacturers, pictures of club events and much much more.

**Club Dues:**

Regular Members ...\$20  
Family Members\* ...\$10  
Teenage Members ..\$10  
Club Badge\*\* .....\$3

Dues run from January thru Dec and are prorated for new members.

\*Additional members in the family of a regular member pay the family rate up to \$30 per family.

\*\*There is a \$1 charge if you'd like to have your badge mailed to you.

## The Antenna Tuner

By Bob Eckweiler – AF6C

(This is part four in a series to explore RF impedance, from the antenna...down the feed line...and eventually reach the antenna tuner and transmitter.)

Last month we saw how the impedance present on a feedline changes as it is measured at different points along that feedline from the antenna to the transmitter. Only when the antenna terminal and the coax impedance are the same, is the impedance constant along the feedline; this is the ideal condition, but is difficult to meet and is lost as soon as the frequency is varied. In practice, one must expect some mismatch and deal with it. A mismatch, when properly handled, won't result in a significant degradation of your signal. This month we'll look at the interface between the radio and the feedline. An antenna tuner is often used here to match the feedline impedance to the transmitter (and cancel out any reactance from the antenna). While the antenna tuner is normally located in the shack, some hams claim that it should be placed at the antenna instead for much superior performance. Later in the article we'll look at the pros and cons of doing this. Please read it before you haul your Johnson Matchbox to the top of your tower!

### A Bit of History:

Older tube transmitters and amplifiers usually had a pi-network output tuning stage that was able to compensate for mismatches that resulted in SWRs up to about 3:1. The pi-network could easily handle the mismatch that occurred across the band on 10, 15 or 20 meters or much of 40 meters when using a properly designed resonant antenna (triband beam, dipole, multiband vertical, etc.) The antenna tuner was only found in shacks where non-resonant antennas (longwires, etc.) or resonant antennas on 80 and 160 meters were used. Why do resonant antennas require an antenna tuner on 160 and 80 meters and not on the higher bands? It's a simple question of antenna bandwidth. Let's say a particular design of an antenna

has an SWR of 1.2:1 at its resonant point and remains below 2:1 as you move in frequency  $\pm 1\%$  from the resonant point. On 15 meters the whole 450 KHz segment of the band is only about 2% of the frequency, so if the antenna is cut somewhere near the middle it should be usable with an SWR never much greater than 2:1 across the band. However, on 80 meters that 2% is only about 70 KHz of the 500 KHz width of the band. Therefore only a small part of the band can be used with an SWR below 2:1. As long as you stay within that 70 KHz area no antenna tuner is required. But hams like to use their available spectrum!

Today's solid-state transmitters commonly use broadband output. When they were first introduced there was a lot of hype about "no tuning needed". While that was true for load impedances very close to the  $50 + j0$  ohm design impedance, larger mismatches often resulted in damage to the expensive final transistors. Protective circuits were quickly developed that lower the power output when a significant SWR is detected to prevent transistor damage. Hams found their power dropping off as they moved around the band away from the antenna resonant point with their new solid state radios. The solution was to add an external antenna tuner to bring the impedance back in line and allow the radio to develop full power. Of course the tuner needed to be tuned so the benefit of "no tuning needed" vanished. Manufacturers quickly compensated by adding "automatic" antenna tuners that could tune at the touch of a switch. These tuners work well but are limited due to size and have matching capabilities on par with the range pi-networks could tune. (It's a credit to the manufacturers design skill that they are able to make them as small as they have!) The Kenwood TS-440SAT antenna tuner is specified to match between 20 and 150 ohms, an SWR of around 3:1. Solid state transmitter have resulted in internal or external antenna tuners once again becoming popular in ham shacks.

### A Look at Power Transfer:

The antenna tuner helps in the process of getting power from the radio to the antenna where it can be radiated. So, what is the most efficient way to transfer power from one point to another along a wire?

-- See **TechTalk** cont'd on page 4 --

**TechTalk** -- cont'd from page 3

Forget RF, forget even AC, we'll do this in as simple a way as we can by using DC - just volts, ohms and amperes! Figure 1 shows a simple DC circuit.




Figure 1

The battery produces 100 volts.  $R_S$  is the source resistance and represents the internal resistance of the battery and the wire.  $R_L$  is the load. This is the resistor we want to absorb the most wattage. With the battery voltage set at 100 volts and  $R_S$  set at 50 ohms, the question is: What is the resistance of  $R_L$  that will allow it to absorb the most power from the battery? This can easily be solved using calculus, but let's keep it simple and use algebra.  $R_L$  is a load resistance.  $I$  is the current flowing through  $R_L$  and is determined by dividing the voltage by the sum of  $R_S$  and  $R_L$  (Ohms Law!):

$$I = \frac{E}{(R_S + R_L)} = \frac{100}{(50 + R_L)}$$

The power dissipated by  $R_L$  is then calculated by:

$$W_L = I^2 R_L$$

Look at Table 1. It solves the preceding equations for various values of  $R_L$ . I've left two rows blank for you to do as an exercise; if you email me with the correct missing values I'll draw a name from the correct answers for a special prize. Answers must be received the day prior to the July meeting. From Table 1, it's evident that the most power is transferred when  $R_L = R_S$ . But even more interesting is how the power transfer falls off away from this point. When the resistance changes by  $\pm 25\%$  the power drops by only about 2%. As long as we're in the vicinity of the 50 ohm resistance the loss will be minimal.

We can now expand our model above to consider AC

and include reactances. Remember that a true reactance doesn't dissipate any power. Instead, it cause a phase shift between the voltage and current flowing in the feedline. Maximum power can only be delivered when the voltage and current are in phase. Thus to get the maximum power transfer the source and load reactances must be equal in magnitude but have opposite signs. If the source has 10 ohms inductive reactance ( $+j10?$ ) then the load must have 10 ohms capacitive reactance to ( $-j10$  ohms) to cancel and bring the phase shift back to zero. Remember here we are talking about short lead lengths.

E	Rs	RL	I	WLoad
Volts	Ohms	Ohms	Amps	Watts
100	50	0.0	2.00	0.00
100	50	5.0	1.82	16.53
100	50	10.0	1.67	27.78
100	50	20.0	1.43	40.82
100	50	35.0	1.18	48.44
100	50	37.6	???	??.??
100	50	40.0	1.11	49.38
100	50	45.0	1.05	49.86
100	50	48.0	1.02	49.98
100	50	50.0	1.00	50.00
100	50	52.0	0.98	49.98
100	50	55.0	0.95	49.89
100	50	60.0	0.91	49.59
100	50	65.0	0.87	49.15
100	50	66.5	???	??.??
100	50	100.0	0.67	44.44
100	50	200.0	0.40	32.00

**Table 1– Watts into LOAD as Rload Varies**

**The Antenna Tuner:**

Let's assume at the transmitter end of the feedline the impedance is  $40 - j42.5$  ohms (an SWR of 2.5:1.) Your solid state rig probably won't handle this load efficiently. By placing a properly adjusted antenna tuner between the rig and the feedline a more efficient match may be obtained. What the antenna tuner must do is present an impedance to the transmitter of  $50 + 0j$  ohms and an impedance to the feedline of  $40 + 42.5j$

-- See **TechTalk** cont'd on page 8 --



"RF"

ORANGE COUNTY AMATEUR RADIO CLUB

JULY 2003

FIELD DAY SUMMARY  
FOR  
THE ORANGE COUNTY AMATEUR RADIO CLUB - W6ZE

by: Ken / W6HHC & Bob / AF6C

YEAR	160M SSB	80M CW	75M SSB	40M CW	40M SSB	20M CW	20M SSB	17M SSB	15M CW	15M SSB	12M SSB	10M CW	10M SSB	6M PHN	2M CW	2M PHN	2M PKT	220 PHN	440 PHN	ATV	SAT- ELLITE	GOTA	---- TOTAL ---- QSO's / (POINTS)
2003	0	0	85	52	127	27	295	0	0	191	0	0	41	52	0	64	0	1	13	0	0	0	948 / 2,054
2002	0	26	69	192	279	76	229	0	0	485	0	0	18	62	0	68	2	6	10	3	0	3	1,528 / 3,648
2001	0	0	25	101	251	0	432	0	0	675	0	0	109	48	0	28	0	1	0	0	3	-	1,673 / 3,548
2000	0	19	20	88	91	0	625	0	0	794	0	0	121	36	0	72	0	7	15	0	1	-	1,889 / 3,992
1999	0	13	20	15	237	0	996	0	0	724	0	0	22	5	0	2	0	0	0	0	0	-	2,034 / 4,124
1998	0	24	75	65	136	100	250	0	0	624	0	0	82	0	0	46	7	17	12	0	1	-	1,439 / 3,270
1997	5	81	131	83	306	150	853	0	14	275	0	0	106	32	0	79	32	4	0	0	1	-	2,152 / 5,024
1996	-	146	228	104	125	283	673	0	40	605	0	0	217	121	0	32	13	0	40	0	1	-	2,628 / 6,428
1995	-	145	272	203	94	443	572	0	51	451	0	0	131	66	0	93	33	29	8	0	6	-	2,597 / 6,944
1994	-	114	114	208	45	486	748	0	85	761	0	13	312	58	0	94	31	33	0	0	0	-	3,102 / 8,078
1993	-	150	100	159	81	530	700	30	131	812	0	0	179	40	0	86	35	12	16	0	0	-	3,061 / 8,132
1992	-	0	294	200	110	541	555	0	0	840	0	0	232	13	0	74	41	0	1	2	80	-	2,983 / 7,530
1991	-	105	308	182	182	400	623	23	9	463	0	0	104	4	0	141	48	23	11	0	0	-	2,626 / 6,740
1990	-	0	0	70	144	0	370	-	0	747	0	0	131	39	0	114	2	14	26	0	-	-	1,657 / 3,454
1989	-	30	0	98	5	0	906	-	21	172	0	0	238	3	0	121	18	24	9	1	-	-	1,646 / 3,590
1988	-	127	0	93	75	2	359	-	0	570	0	144	81	0	0	32	14	0	-	-	-	-	1,497 / 3,726
1987	-	22	0	0	39	0	708	-	0	18	1	117	0	1	0	51	5	0	-	-	-	-	962 / 2,202
1986	-	0	46	219	78	0	488	-	0	45	10	0	0	0	0	82	0	0	-	-	-	-	968 / 2,374
1985	-	85	0	315	91	35	662	-	78	0	-	0	0	0	0	22	-	0	-	-	-	-	1,288 / 3,602
1984	-	18	0	313	0	32	196	-	32	350	-	0	0	0	0	0	-	0	-	-	-	-	941 / 2,672
1983	-	3	93	200	0	0	776	-	0	995	-	0	43	18	0	16	-	1	-	-	-	-	2,145 / 4,696
1982	-	0	105	59	238	40	352	-	19	515	-	0	72	0	0	155	-	27	-	-	-	-	1,582 / 3,400
1981	-	0	167	200	265	60	699	-	77	717	-	0	105	0	0	197	-	0	-	-	-	-	2,487 / 5,648
1980	-	20	149	205	235	471	318	-	52	1,025	-	0	226	12	0	100	-	36	-	-	-	-	2,849 / 7,194
1979	-	0	195	198	92	42	773	-	0	737	-	0	95	0	2	124	-	8	-	-	-	-	2,266 / 5,016
1978	-	16	196	246	170	30	981	-	57	558	-	13	145	0	1	164	-	23	-	-	-	-	2,600 / 5,926
1977	-	25	243	182	199	0	843	-	81	486	-	4	309	0	4	234	-	0	-	-	-	-	2,610 / 5,812
1976	-	99	254	152	487	21	600	-	64	210	-	2	54	0	0	2	-	0	-	-	-	-	1,945 / 4,566
1975	-	80	120	154	274	40	863	-	140	259	-	0	123	0	0	0	-	0	-	-	-	-	2,053 / 4,934
1974	-	6	161	6	333	0	630	-	12	342	-	0	110	0	0	0	-	0	-	-	-	-	1,600 / 3,248
1973	-	90	226	0	452	0	932	-	0	273	-	0	0	0	0	46	-	0	-	-	-	-	2,019 / 4,218
1972	-	0	50	0	350	0	521	-	0	530	-	0	0	0	0	94	-	0	-	-	-	-	1,545 / 3,090
1971	-	0	274	0	106	0	530	-	0	136	-	0	0	0	0	0	-	0	-	-	-	-	1,046 / 2,092
1970	-	0	272	0	0	0	531	-	0	426	-	0	0	0	0	0	-	0	-	-	-	-	1,229 / 2,458
1969	-	0	98	0	50	0	375	-	0	301	-	0	0	0	0	169	-	0	-	-	-	-	993 / 1,986
1968	-	10	224	62	396	93	328	-	24	430	-	0	68	0	0	145	-	0	-	-	-	-	1,780 / 3,938

Note: These are raw contacts taken directly from the log sheets. Adjustments have not been made for duplicate contacts, and bonus points have not been added yet. Final scores appear in QST.

## OCARC General Meeting Minutes

June 20, 2003

June General meeting OCARC was held 6/20/03 at the American Red Cross East Building. The meeting called to order at 7:00pm by President Lowell KQ6JD. There were a total of 25 members and visitors present. The following guests were recognized: Carl WA6BSV (ex-KG6KYJ), Jack N6UC a Past President of OCARC, & Steve KG6QVY.

Welcome to all--Please come often.

Roll Call showed the following officers absent: Phil N7PA; Matt K7LNX; Cory AE6GW and Frank WA6VKZ, a quorum being present.

**Wouff Hong:** OCARC has been asked to do the Wouff Hong ceremony at the SW Division Convention 9/99/03. After a brief discussion the matter was tabled until the 7/5/03 board meeting.

**Treasurers Report:** \$2507.35 in the bank.

**OC Fair:** OCARC will man the booth Wednesday July 16. Bob KD6BWH passed around the sign up sheet

Motion: W7KTS moved that OCARC give \$50.00 to OCCARO to help cover the cost of the booth. Ken K6HHC seconded. Discussion followed and motion passed.

**Program:** Ken K6HHC was introduced and gave a slide presentation of past OCARC Field Days and explained the purpose of Field Day. He also reviewed the FD set-up schedule for Saturday and fielded planning questions.

The meeting adjourned at 8:45 pm.

Respectfully Submitted,  
David Mofford W7KTS - Secretary

---

## OCARC BOARD MINUTES

July 05, 2003

The OCARC Board Meeting held July 5, 2003 at Cowgirls Cafe, Too. Called to order at 8:30AM by Pres. Lowell KQ6JD. There were a total of 13 members and visitors present. Roll Call indicated 6 directors were present; a quorum being available.

**V.P.** - The program for July will be Joe Moell, KØOV, speaking on T-Hunts

**Secretary** -Nothing to report

**Treas:** \$2436.12 in the account. Phil N7PA announced he is stepping down as Treasurer due to the demands on his schedule. The club needs a new Treasurer!!!

**Membership:** 48 members

**Activities:** Nothing to report

### Old Business:

**Bylaws:** Phil N7PA steps down as Chair and Frank WA6VKZ resigned as a member. Pres. Lowell accepted the committees work and terminated the committee's existence. Pres. Lowell thanked Phil N7PA for his work and service to the club and in particular the time, effort and availability he has shown to Frank WA6VKZ.

**Field Day:** Ken W6HHC gave an accounting of Field Day contacts:

BAND----QSOs	BAND----QSOs
440 13	20SSB 295
220 1	20CW 27
2m 64	40SSB 127
6m 52	40CW 52
10SSB 41	75SSB 85
15SSB 191	

Plus 2 new Members

**Wouff Hong:** Needed: 1 person to head up ceremony practices and to secure costumes. Tabled until July Regular Meeting.

### New Business:

Motion by David W7KTS, seconded by Steve KB1GZ to cancel September Board meeting due to SW Division Convention. Passed.

Meeting Adjourned 8:55AM.

Respectfully Submitted,  
David Mofford W7KTS - Secretary

---

## TechTalk -- cont'd from page 4

ohms. The plus sign is not a typo! We want to match the resistive component of the impedance but instead of matching the reactive component we want an equal but opposite reactance. In mathematics a number such as  $40 - j42.5$  is called a "complex number"; and every complex number has a "conjugate" which is identical except the sign of the "j" (reactive) term is reversed. The conjugate of  $40 - j42.5$  is  $40 + j42.5$ .

Why is the opposite reactance required? Remember last month we discussed how impedance varies along a transmission line. At the antenna, the transformed conjugate reactive part of the impedance is equal but opposite to the reactive component at the antenna terminals. Since these reactance add, the reactive component becomes zero. Is this tuning the antenna? Well, the SWR along the coaxial line is still the same, but the antenna is operating efficiently because the reactance is canceled. I'll leave the debate as to whether an antenna tuner really tunes the antenna to others, but what is tuned is the whole antenna system (antenna, feedline and the antenna tuner in combination.) The antenna tuner, when properly adjusted, transforms the complex impedance of the antenna and feedline to the 50 ohms resistive that the transmitter needs to put out its maximum energy. It also provides a conjugate component that allows the antenna to operate efficiently.

### Real Antenna Tuners:

There is one caveat; an improperly adjusted antenna tuner can result in a large loss of power to the antenna. Two or more different sets of adjustments can result in a proper match, but with significantly different efficiencies. The loss will take on the form of heat or arcing in the antenna tuner and can result in damaged coils, capacitors, and switch contacts. It is best to follow the recommendations of the antenna tuner manufacturer to obtain the most efficient match. Unfortunately, the versatility of an antenna tuner that can match a wide range of impedances also increases the possibilities of misadjustment. For further information you might want to read part one of W8ZR's

-- See **TechTalk** cont'd on page 9--

## OCARC Needs New Treasurer

As reported in the Board Minutes this month, Phil N7PA has resigned as club Treasurer because of demands on his time. (As Phil said..."I can't make the meetings!")

We need someone who willing to fill-in during the last 6 months of this year. Please give our president, Lowell, a call at (714) 997-0999 if you are willing to help out.

.....de Lowell KQ6JD "El Presidente"

## Local OC Ham wins "Young Ham of the Year" Award

Rich Thompson WA6NOL, a frequent check-in to our OCARC Nets announced that his 17-year-old son Jay W6JAY had been chosen for the "2003 Young Ham of the Year" award.

Jay is very active and well-known in ARDF contests on a world-wide basis, he is a MARS operator, involved in the HDSCS emergency group, and is the youngest ARRL Official Observer (OO) in history. Jay just graduated from High School and plans to go to UCI for Computer Science and earn two concurrent degrees at the same time!

In the 20 years of the "Young Ham of the Year" awards, this is the first time that a "West Coast" Ham has won the award. Jay with his proud father will receive the award at the Huntsville Ham Convention on August 15.

Congratulations, Jay Thompson W6JAY!!

---



*The EZ-Tuner* in the April 2002 issue of QST (pages 40 through 44.) The author does a good job of discussing the trade-offs of the modern antenna tuner as well as giving some interesting history.

#### Antenna Tuners at the Antenna:

Some amateurs advocate putting the antenna tuner at the other end of the feedline, so it is located right at the antenna. This does have an advantage and also lots of disadvantages. The advantage is that when the tuner is properly adjusted, the impedance along the feedline will be match the feedline impedance and the SWR will be the ideal 1:1. This means that the additional loss in the feedline due to SWR will be eliminated. Unless the SWR is very large (in which case you should think about using a twin lead type of feedline) this loss is small. For example if your feedline has a nominal loss of 1.0 dB the added loss due to an SWR of 5:1 would be only about another 1 dB.

The disadvantages are obvious. Weatherproofing, remote control or automatic adjusting systems, remote indicators, electrical power to the tuner all have to be coped with. The "Law of Vanishing Returns" should be studied carefully before considering placing the antenna tuner at the antenna. There are some remote tuners that are available commercially that can do the job. I've had a good experience with an SGC unit, but read the specifications carefully before you buy.

The antenna matching circuit, often used right at the feedpoint on an antenna, is a form of antenna tuner! The idea of the antenna matching circuit is to convert the impedance of an antenna to an impedance that is close to that desired to match the feedline. Of course, these devices are usually impracticable to adjust once the antenna is installed; but they do present a better impedance to the feedline to lower the SWR and make the antenna tuner's job easier.

Next month TechTalk will take a look at baluns and RF Chokes and, space permitting, we'll begin discussion of SWR and its more professional equivalent: Reflection Coefficient.

73, de AF6C

---

### BPL Interference is Threat to HAMS

Broadband-over-Power-Line ("Access BPL") is a technology being promoted by utility companies to feed broadband signals onto power lines using high frequency RF from 2-to-80 MHz.

The benefit is that fast Internet access (just like DSL) arrives to your house right on the electrical power lines. ...and power lines are everywhere!!

The bad news is that the broadband signals from the power lines will be radiating right on top of 80M, 20M and every popular ham band all the way up to 6M. And it is not just the ham bands, short-wave listeners are at risk too. These BPL signals could transform HF from a quiet haven that hams enjoy into a noisy industry wasteland .....and power lines are everywhere!!!

The ARRL Spectrum Defense Fund is sending the message..."**No! You will not make our frequencies useless!**"

Go to [www.ARRL.org](http://www.ARRL.org) to learn more about BPL issue and what you can do.

### Keep Morse Code Requirement??

Prior to July 5, 2003, ITU member countries were required to administer a Morse Code test to applicants seeking Amateur Radio HF privileges. On July 5, 2003, that international requirement changed so that each individual administration now may decide for itself whether or not to require a Morse Code test.

What is your view on this issue? Should the FCC keep some sort of Morse Code test/demonstration as a part of future General and Extra class license exams?

**Art Goddard W6XD says the ARRL wants to know the OCARC's club viewpoint. (Note: the ARRL will also accept views from individual hams ...but the ARRL wants views from HAM Clubs.)**

### QUOTES from FIELD DAY 2003

"I think that everybody at Field Day worked well together as a team. I got several compliments by visitors on just how well everybody chipped in helping on the set up and tear down. Looking forward to next year." ....de Lowell KQ6JD

(PS: May the Band Gods be better next year)

"VHF and UHF were great. I only operated USB to get my contacts. It feels more like a contest to use USB, but a point is a point....so I was ready to use FM if needed. With HF, there are always new stations to work as propagation moves around the world. On VHF (unless 6m opens) the area of propagation never changes, and you can only hear the same stations. That was just fine since there was much local activity. Thanks to all of the IC706 and FT100 and all of the other all mode VHF capable rigs out there, there was enough activity above 50MHz."....de Chris KE6LEX

"The fifteen meter band conditions were the worst I've seen in 43 years of Field Days. Fried, Sandy and the ARRL gang showed perfect timing showing up for the W6NGO annual toast and remembrance! The Club web page resulted in visitors showing up to join our operation, including Bill N4WRC visiting from Pell City, AL." ....de Bob AF6C

"What a great year for Field Day interaction with the public and with our club members. I was the 20 meter band captain in name only. Other than helping put on a lunch for the team, along with Ken and his team for 15 meters, I really had a back seat job. This year 20 meters was actually run by John-WB6AJE and Howard-WB6TKK. They had a super 20 meter station set up in no time. That left me time to visit with guests that stopped by to see what in the heck we were doing, plus fill in some time on an empty 80 meter station late at rite. Too bad the band conditions weren't great; we were all set to rack up the contacts!"....de Bob KD6BWH

"40M band was extremely noisy. A local ham stopped by and confirmed that local noise has been a problem. 80 meters was dead during the day, but came alive at night. Both 40M & 80M antennas worked well and were easy to erect. FD teardown went very well and in record time."....de Larry K6VDP

"I had a really great time in Southern CA at Field Day. I was exposed to a lot of new types of radio communication. So far, I have just been phone on 2 meter and 70 cm. The ATV and slow scan TV has really got my attention. I really learned a lot at Field Day. Thanks for your hospitality and letting me participate in the events.".....de Bill N4RWC, visitor from Alabama

"I had a great time at FD. Terrific turn out!! Probably had 45 members and visitors. Things ran smoothly. Worst 15M and 10M propagation conditions that I can remember...but my friend Art Goddard W6XD explained that the ARRL is working on a "5-year plan" to improve propagation...I bet it will work!!"....de Ken W6HHC

"I for one had an absolutely wonderful time, and thanks to everyone who made it so!"....de Steve KB1GZ

---

**ORANGE COUNTY AMATEUR RADIO CLUB, INC**  
**P.O. BOX 3454**  
**TUSTIN, CA 92781-3454**

***First Class Mail***

***Time Dated Material.***

***Please Expedite!!***

**July 2003 - RF Page 10**

---